


<p>(51) International Patent Classification <sup>6</sup> : H04B 3/23, 3/03, H04M 11/06</p>	<p>A1</p>	<p>(11) International Publication Number: WO 98/12824 (43) International Publication Date: 26 March 1998 (26.03.98)</p>
<p>(21) International Application Number: PCT/FI97/00566 (22) International Filing Date: 22 September 1997 (22.09.97) (30) Priority Data: 963791 23 September 1996 (23.09.96) FI (71) Applicant (for all designated States except US): TELLABS OY [FI/FI]; Sinikalliontie 7, FIN-02630 Espoo (FI). (72) Inventor; and (75) Inventor/Applicant (for US only): LAAMANEN, Heikki [FI/FI]; Nuottakuninkaantie 3 B, FIN-02230 Espoo (FI). (74) Agents: LAINE, Seppo et al.; Seppo Laine Oy, Lönnrotinkatu 19 A, FIN-00120 Helsinki (FI).</p>		<p>(81) Designated States: AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, CA, CH, CN, CU, CZ, DE, DK, EE, ES, FI, GB, GE, GH, HU, ID, IL, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MD, MG, MK, MN, MW, MX, NO, NZ, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, UA, UG, US, UZ, VN, YU, ZW, ARIPO patent (GH, KE, LS, MW, SD, SZ, UG, ZW), Eurasian patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, ML, MR, NE, SN, TD, TG).</p> <p><b>Published</b> <i>With international search report. Before the expiration of the time limit for amending the claims and to be republished in the event of the receipt of amendments.</i></p>

(54) Title: MULTISPEED MODEM WITH ECHO-CANCELLING BY MEANS OF AN INTEGRATOR IN A FEEDBACK PATH



**(57) Abstract**

The invention relates to a circuit configuration and a method for adapting an echo-cancelling multispeed modem to a line. The circuit configuration comprises a transmitter (1), a transmitter buffer (3) connected on the signal path of the transmitter (1), a line drive resistance (17) connected to the output of the transmitter buffer (3), a line transformer (8) connected to the line drive resistance (17), and echo-cancelling elements (5, 6, 7) for eliminating the transmit signal echo from the receive signal. According to the invention, to the input of the transmitter buffer (3) is arranged a feedback path from the connection point of the line transformer (8) and the line drive resistance (17) by means of an integrator (9).

**FOR THE PURPOSES OF INFORMATION ONLY**

Codes used to identify States party to the PCT on the front pages of pamphlets publishing international applications under the PCT.

AL	Albania	ES	Spain	LS	Lesotho	SI	Slovenia
AM	Armenia	FI	Finland	LT	Lithuania	SK	Slovakia
AT	Austria	FR	France	LU	Luxembourg	SN	Senegal
AU	Australia	GA	Gabon	LV	Latvia	SZ	Swaziland
AZ	Azerbaijan	GB	United Kingdom	MC	Monaco	TD	Chad
BA	Bosnia and Herzegovina	GE	Georgia	MD	Republic of Moldova	TG	Togo
BB	Barbados	GH	Ghana	MG	Madagascar	TJ	Tajikistan
BE	Belgium	GN	Guinea	MK	The former Yugoslav Republic of Macedonia	TM	Turkmenistan
BF	Burkina Faso	GR	Greece	ML	Mali	TR	Turkey
BG	Bulgaria	HU	Hungary	MN	Mongolia	TT	Trinidad and Tobago
BJ	Benin	IE	Ireland	MR	Mauritania	UA	Ukraine
BR	Brazil	IL	Israel	MW	Malawi	UG	Uganda
BY	Belarus	IS	Iceland	MX	Mexico	US	United States of America
CA	Canada	IT	Italy	NE	Niger	UZ	Uzbekistan
CF	Central African Republic	JP	Japan	NL	Netherlands	VN	Viet Nam
CG	Congo	KE	Kenya	NO	Norway	YU	Yugoslavia
CH	Switzerland	KG	Kyrgyzstan	NZ	New Zealand	ZW	Zimbabwe
CI	Côte d'Ivoire	KP	Democratic People's Republic of Korea	PL	Poland		
CM	Cameroon	KR	Republic of Korea	PT	Portugal		
CN	China	KZ	Kazakhstan	RO	Romania		
CU	Cuba	LC	Saint Lucia	RU	Russian Federation		
CZ	Czech Republic	LI	Liechtenstein	SD	Sudan		
DE	Germany	LK	Sri Lanka	SE	Sweden		
DK	Denmark	LR	Liberia	SG	Singapore		
EE	Estonia						

MULTISPEED MODEM WITH ECHO-CANCELLING BY MEANS OF AN INTEGRATOR IN A  
FEEDBACK PATH

The present invention relates to a circuit configuration  
5 according to the preamble of claim 1 for adapting an  
echo-cancelling modem to a line.

The invention also concerns a modem adaptation method.

10 Conventionally, a modem is connected to a line via a  
transformer which isolates the line galvanically from the  
modem and serves as an overvoltage protection against  
transients imposed on the modem from the line. The  
transformer inductance of an echo-cancelling modem must  
15 be held within certain limits in order to keep the number  
of weighting coefficients of the digital echo-cancelling  
circuit sufficiently small as evaluated against to the  
implementation costs of the echo canceller, and on the  
other hand, to prevent the transformer from imposing  
20 excessive distortion on received signal, thus deteriorat-  
ing the function of the modem receiver circuitry. In the  
prior art, adjustment of the transformer inductance has  
been problematic in multispeed modems, wherein the  
selection of an optimal inductance for each data transfer  
25 speed has required the use of, e.g., multiwinding trans-  
formers as well as relay or switch control circuits  
thereof.

It is an object of the present invention to overcome the  
30 drawbacks of the above-described technique and to provide

an entirely novel type of circuit configuration for adapting an echo-cancelling modem to a line.

5 The goal of the invention is achieved by providing with the help of an integrator in front of the transformer a feedback circuit in which, by virtue of a controlled time constant, the line transformer inductance can be adjusted dynamically according to the instantaneous data transfer speed using, e.g., a simple switched resistor matrix.

10

More specifically, the circuit configuration according to the invention is characterized by what is stated in the characterizing part of claim 1.

15 Furthermore, the method according to the invention is characterized by what is stated in the characterizing part of claim 9.

The invention offers significant benefits.

20

The digital circuit section associated with echo cancellation can be fabricated at a lower cost. The transformer matching circuit is realized without expensive multi-winding transformers and relay circuits required for  
25 their switching arrangements that are both costly and prone to malfunction.

In the following, the invention will be examined in greater detail with the help of exemplifying embodiments  
30 illustrated in the appended drawings in which

Figure 1 shows the block diagram of a circuit configuration according to the prior art;

Figure 2 shows the block diagram of a circuit configuration according to the invention;

Figure 3 shows a detail of the circuitry of Fig. 2; and

Figure 4 shows an alternative implementation of the circuit detail of Fig. 2.

Referring to Fig. 1, conventionally the signal from the transmitter 1 of an echo-cancelling multispeed modem is taken to a digital/analog converter 2, after which the analog output signal is buffered by a buffer amplifier 3, called the transmitter buffer. The circuitry, which comprises an isolation amplifier 4, impedances 15, 16 and 17 as well as the impedance  $Z = sL \parallel Z_L$  formed by the transformer 8 and the line, perform in an echo-cancelling modem as a conventionally used hybrid circuit which cancels a portion of the reflected echo of the transmit signal ( $s$  denotes the variable of Laplace transform). The hybrid acts as a Wheatstone bridge, where the impedance 16 connected at its one end to the transmitter buffer 3 and the impedance 15 connected between the first impedance and the ground form the other branch of the bridge, while the impedance 17 connected at its one end to the transmitter buffer 3 and the impedance  $sL \parallel Z_L$  formed together by the transformer 8 and the line perform as the other branch of the bridge. The impedance 17 connected

between the transmitter buffer 3 and the transformer 8 may also be called the line drive impedance. The hybrid attenuates the transmit signal echo the better the closer the impedance 15 is the resultant impedance of the transformer and the line, that is, the parallel connected impedance  $sL \parallel Z_L$  of the main impedance  $L$  of the transformer 8 and the line impedance  $Z_L$ . Both the receive signal and the residual transmit signal echo are taken from the amplifier 4 for digitization to the analog/digital converter 5. While the above-described hybrid configuration is representative to a conventional embodiment, other circuit embodiments implementing the transfer function corresponding to the bridge branch formed by the impedances 15 and 16 may be contemplated without compromising performance of the invention.

As the parallel-connected impedance  $sL \parallel Z_L$  of the transformer 8 and the line form one of the bridge impedances, the magnitude of the inductance  $L$  of the transformer 8 has such an effect on the transmit signal echo that if the transformer inductance is too high, the duration of the echo path impulse response (echo tail) increases from a normal situation, whereby efficient echo cancellation requires a greater number of weighting coefficients in the adaptive echo cancellation circuit, resulting a higher component cost. In the case that the transformer inductance  $L$  is too small, the transformer imposes distortion on the receive signal from the line, thereby deteriorating the function of the receiver.

The digitized signal is taken to a summing point 6, where it is summed for echo cancellation with the inverted receive signal taken from the transmitter 1 via an adaptive FIR filter. Thus, a signal component processed by the  
 5 filter 7 is subtracted from the receive signal in order to cancel the transmit signal echo, whereby the output 20 of the summing stage 6 delivers the echo-free modem output signal.

10 By denoting the resistance 17 with symbol R for the sake of simplicity, the transfer function of a circuit configuration according to the prior art can be computed from the diagram of Fig. 1:

$$\frac{V_o}{V_i} = \frac{sL \parallel Z_L}{R + sL \parallel Z_L} = \frac{1}{1 + \frac{R}{sL \parallel Z_L}} = \frac{1}{1 + R \left( \frac{1}{sL} + \frac{1}{Z_L} \right)} \quad (1)$$

15

This equation may further be written:

$$\frac{V_o}{V_i} = \frac{s}{s \left( 1 + \frac{R}{Z_L} \right) + \frac{R}{L}} \quad (2)$$

In the circuit configuration according to the invention illustrated in Fig. 2, the feedback path is formed by  
 20 means of an integrator 9 from the connection point of the line drive impedance 17 and the primary winding of the transformer 8 to the input of the transmitter buffer 3.

As the integrator 9 represents a term  $-A/s$ , the transfer function of the circuit configuration according to the invention comprising the integrator 9 may be written from point  $V_x$  to point  $V_o$  as follows:

$$V_x = V_i - \frac{A}{s} \cdot V_o \quad (3)$$

This equation may further be rewritten:

$$V_o = \frac{Z}{R+Z} \cdot V_x = \frac{Z}{R+Z} \left[ V_i - \frac{A}{s} \cdot V_o \right] \quad (4)$$

Rewriting the equation gives:

$$\left( 1 + \frac{A}{s} \cdot \frac{Z}{R+Z} \right) V_o = \frac{Z}{R+Z} \cdot V_i \quad (5)$$

which may be further rewritten as:

$$\frac{V_o}{V_i} = \frac{\frac{Z}{R+Z}}{1 + \frac{A}{s} \cdot \frac{Z}{R+Z}} = \frac{sZ}{s(R+Z) + AZ} \quad (6)$$

When the resultant impedance  $Z$  is divided into a parallel connection of the transformer impedance  $L$  and the line impedance  $Z_L$  in the following manner:

$$\frac{1}{Z} = \frac{1}{sL} + \frac{1}{Z_L} \quad (7)$$

which the transfer function can be written as:



$$\frac{V_o}{V_i} = \frac{s}{s(1 + \frac{R}{Z}) + A} = \frac{s}{s(1 + \frac{R}{sL} + \frac{R}{Z_L}) + A} \quad (8)$$

which may further be rewritten as:

$$\frac{V_o}{V_i} = \frac{s}{s(1 + \frac{R}{Z_L}) + \frac{R}{L} + A} \quad (9)$$

A comparison of the transfer functions represented by Eqs. 2 and 9 reveals that Eq. 9 can be rewritten as:

$$\frac{V_o}{V_i} = \frac{s}{s(1 + \frac{R}{Z_L}) + \frac{R}{L} \cdot (1 + \frac{AL}{R})} \quad (10)$$

Here, the transformer inductance is seen to be virtually  
5 reduced to a value of:

$$L - \frac{L}{1 + A \cdot \frac{L}{R}} \quad (11)$$

Obviously, the coefficient A of the integrator 9 can be used for controlling said inductance.

The integrator 9 can be implemented in a plurality of al-  
10 ternative methods either using a continuous-signal operational amplifier or a discrete-signal filter known in the art as the "switched-capacitor circuit", whereby the coefficient A may be easily adjusted.

In Fig. 3 is shown a continuous-signal operational amplifier configuration, in which the time constant  $RC$  is the inverse of the coefficient  $A$ . Hence, the circuit 9 of Fig. 3 comprises an operational amplifier 10 having its output terminal connected via a capacitor 11 to the inverting input of the operational amplifier 10. A resistor 12 with a capacitor 11, both connected to the inverting input terminal of the amplifier, determine the integration time constant of the integrator. Thus, said time constant is a product of said components, and therefore, the inverse of said coefficient  $A$ .

In practice, the coefficient  $A$  is adjusted by, e.g., selecting the value of the resistance 12 according to the modem data transfer speed from a resistor matrix (by means of solid-state switches, for instant). Then, the value of the capacitor 11 is kept unchanged. Alternatively, the capacitor 11 can be selectable from a switched capacitor matrix, whereby the value of the resistor 12 is kept unchanged.

In Fig. 4 is shown an integrator embodiment implemented using the "switched-capacitor" technique, in which the value of  $KC_2/C_1$  is the inverse of the coefficient  $A$ . Herein,  $K$  is a coefficient dependent on the frequency of the clocks driving the solid-state switches SW1-SW4. In the diagram,  $\phi_1$  and  $\phi_2$  denote clock signal of opposite phase that control the solid-state switches SW1-SW4. Thence, the coefficient  $A$  can be altered by either changing said clock frequency or implementing the

capacitors  $C_1$  and  $C_2$  as a capacitor matrix controlled by solid-state switches.

## Claims:

1. A circuit configuration for adapting an echo-cancelling multispeed modem to a line, said circuit  
5 comprising

- a transmitter (1),
- 10 - a transmitter buffer (3) connected on the signal path of the transmitter (1),
- a line drive resistance (17) connected to the output of the transmitter buffer (3),
- 15 - a line transformer (8) connected to the line drive resistance (17), and
- echo-cancelling elements (5, 6, 7) for eliminating the transmit signal echo from the  
20 receive signal,

c h a r a c t e r i z e d in that

- 25 - to the input of the transmitter buffer (3) is arranged a feedback path from the connection point of the line transformer (8) and the line drive resistor (17) by means of an integrator (9).

2. A circuit configuration as defined in claim 1,  
c h a r a c t e r i z e d in that said integrator (9) is  
implemented by means of continuous-signal operational  
amplifier circuit having the time constant (A) of the  
5 integrator (9) made controllable.

3. A circuit configuration as defined in claim 1,  
c h a r a c t e r i z e d in that said integrator (9) is  
implemented by means of discrete-signal operational  
10 amplifier circuit having the time constant (A) of the  
integrator (9) made controllable.

4. A circuit configuration as defined in claim 1,  
c h a r a c t e r i z e d in that the time constant  
15 control of said integrator (9) is implemented by means of  
a resistor or capacitor matrix controlled by solid-state  
switches.

5. A circuit configuration as defined in claim 1,  
20 c h a r a c t e r i z e d in that said integrator (9)  
includes a controllable resistor (12) for setting the  
time constant of said integrator.

6. A circuit configuration as defined in claim 1,  
25 c h a r a c t e r i z e d in that said integrator (9)  
includes a controllable capacitor (11) for setting the  
time constant of said integrator.

7. A circuit configuration as defined in claim 3,  
30 c h a r a c t e r i z e d in that said integrator (9)

includes a controllable capacitor ( $C_1$  or  $C_2$ ) for setting the time constant of said integrator.

8. A circuit configuration as defined in claim 3,  
5 c h a r a c t e r i z e d in that said integrator (9) includes a means for controlling the clock frequency of said controllable switches (SW1-SW4).

9. A method of adapting such an echo-cancelling multi-  
10 speed modem to a line which modem comprises

- a transmitter (1),
- a transmitter buffer (3) connected on the  
15 signal path of the transmitter (1),
- a line drive resistance (17) connected to the output of the transmitter buffer (3),
- a line transformer (8) connected to the line  
20 drive resistance (17), and
- echo-cancelling elements (5, 6, 7) for eliminating the transmit signal echo from the  
25 receive signal,

c h a r a c t e r i z e d in that

- to the input of the transmitter buffer (3) is  
30 arranged a feedback path from the connection

point of the line transformer (8) and the line drive resistor (17) by means of an integrator (9).

5 10. A method as defined in claim 9, c h a r a c t e r -  
i z e d in that said integrator (9) is implemented by means of continuous-signal operational amplifier circuit having the time constant (A) of the integrator (9) made controllable.

10 11. A method as defined in claim 9, c h a r a c t e r -  
i z e d in that said integrator (9) is implemented by means of discrete-signal operational amplifier circuit having the time constant (A) of the integrator (9) made controllable.

15 12. A method as defined in claim 9, c h a r a c t e r -  
i z e d in that said integrator (9) includes a controllable resistor (12) for setting the time constant of said integrator.

20 13. A method defined in claim 9, c h a r a c t e r -  
i z e d in that said controllable resistor (12) is an electronically switched resistor matrix.

25 14. A method as defined in claim 9, c h a r a c t e r -  
i z e d in that said time constant (A) is controlled by altering the clock frequency of said controllable switches (SW1-SW4).

1/4




Fig. 1



2/4




Fig. 2

3/4




Fig. 3

4/4




Fig. 4

## INTERNATIONAL SEARCH REPORT

International application No.  
PCT/FI 97/00566

<b>A. CLASSIFICATION OF SUBJECT MATTER</b>		
IPC6: H04B 3/23, H04B 3/03, H04M 11/06 According to International Patent Classification (IPC) or to both national classification and IPC		
<b>B. FIELDS SEARCHED</b>		
Minimum documentation searched (classification system followed by classification symbols)		
IPC6: H04B, H04L, H04M		
Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched		
SE,DK,FI,NO classes as above		
Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)		
WPI, EPODOC		
<b>C. DOCUMENTS CONSIDERED TO BE RELEVANT</b>		
Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	EP 0691771 A2 (ROCKWELL INTERNATIONAL CORPORATION), 10 January 1996 (10.01.96), column 4, line 11 - line 37; column 8, line 12 - line 51, figure 3  --	1-14
A	US 4888762 A (MASANOBU ARAI), 19 December 1989 (19.12.89), figures 1,3,5, see the whole document  --	1-14
A	US 5222084 A (YUTAKA TAKAHASHI), 22 June 1993 (22.06.93), column 1, line 12 - line 68; column 2, line 1 - line 68; column 3, line 1 - line 48, figure 3  --	1-14
<input checked="" type="checkbox"/> Further documents are listed in the continuation of Box C. <input checked="" type="checkbox"/> See patent family annex.		
<p>* Special categories of cited documents:</p> <p>"A" document defining the general state of the art which is not considered to be of particular relevance</p> <p>"E" earlier document but published on or after the international filing date</p> <p>"L" document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)</p> <p>"O" document referring to an oral disclosure, use, exhibition or other means</p> <p>"P" document published prior to the international filing date but later than the priority date claimed</p> <p>"T" later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention</p> <p>"X" document of particular relevance: the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone</p> <p>"Y" document of particular relevance: the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art</p> <p>"&amp;" document member of the same patent family</p>		
Date of the actual completion of the international search		Date of mailing of the international search report
2 March 1998		09 -03- 1998
Name and mailing address of the ISA/ Swedish Patent Office Box 5055, S-102 42 STOCKHOLM Facsimile No. +46 8 666 02 86		Authorized officer  Göran Magnusson Telephone No. +46 8 782 25 00

## INTERNATIONAL SEARCH REPORT

International application No.

PCT/FI 97/00566

## C (Continuation). DOCUMENTS CONSIDERED TO BE RELEVANT

Category*	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
A	US 5204854 A (ROUBIK GREGORIAN ET AL), 20 April 1993 (20.04.93), figure 6, Detailed description  --	1-14
A	US 5371789 A (AKIHIRO HIRANO), 6 December 1994 (06.12.94), see the whole document  -- -----	1-14

**INTERNATIONAL SEARCH REPORT**  
Information on patent family members

03/02/98

International application No.  
PCT/FI 97/00566

Patent document cited in search report			Publication date	Patent family member(s)		Publication date
EP	0691771	A2	10/01/96	JP	8065217 A	08/03/96
				US	5541990 A	30/07/96
<hr/>						
US	4888762	A	19/12/89	JP	64000827 A	05/01/89
<hr/>						
US	5222084	A	22/06/93	CA	2045250 A,C	26/12/91
				DE	69103977 D,T	13/04/95
				EP	0464500 A,B	08/01/92
				JP	4054718 A	21/02/92
<hr/>						
US	5204854	A	20/04/93	WO	9304539 A	04/03/93
<hr/>						
US	5371789	A	06/12/94	CA	2088558 A	01/08/93
				EP	0561133 A	22/09/93
				JP	5218906 A	27/08/93
<hr/>						